

OPTIONAL ACCESSORIES

ENGINE OIL
ULTRA
PERFORMANCE
LONGLIFE SAE
5W-40
500 ml



Article number: 3906100701
Barcode: 4014915073512



INVERTER GENERATOR 3400 W

- Sturdy and robust steel frame protects vital components
- Max 5.1 HP petrol engine with easy pull start system
- 3400 W maximum power output – 3000 W continuous output
- Built-in energy-saving mode saves fuel and ensures low emissions
- 7.4 litre fuel tank
- Low noise level of 65,5 dB(A)*
*Noise levels may vary depending on distance and location and were measured at 25% load and at a distance of 7 meters from the control panel.



Max. 5.1 HP petrol engine
with pull start system

INCLUDED



Variable
transport handle

SPECIFICATIONS - ENGINE

Model	Single-cylinder; 4 stroke petrol engine
Max. engine power	5.1 HP
Displacement	212 cc
Starter	Electric starter & pull starter
Tank capacity	7.4 L
Fuel consumption load	2.1 L/h

SPECIFICATIONS - GENERATOR

Dimensions L x W x H	579 x 425 x 443 mm
Voltage control	Inverter
Rated output / max. output	3000 / 3400 W
Socket	2 x 230 V~
AC frequency	50 Hz
Overload protection	Yes
Low oil warning	Yes
Voltmeter	Yes

LOGISTICAL DATA

Weight net / gross	43.8 kg / 47 kg
Packaging dimensions	580 x 508 x 450 mm
Article number	5906217901
Barcode	4046664072362
20 Container	180 pcs
40 Container	380 pcs
40 HQ Container	475 pcs



SELF-SUFFICIENT ENERGY SUPPLY
SUITABLE FOR


Camping



Garden shed



Heating system



Refrigerator



Event



Construction site



Laptop



Mobile phone



LOW NOISE



User-friendly operation via
LCD display

3400 W max. power

Fuel tank capacity: 4 L



Robust and noise-insulated
machine housing

Easy to manoeuvre thanks to
movable transport handle



Low noise level of 65,5 dB, at 7 m distance.
Comparable ones are at 95 dB



super silent,
only 65,5 dB

PRODUCT DETAILS

Lasting



2 x 230 V power outlet



Oil warning indicator



Energy saving switch



Overload protection



Fuel-saving



Digital display



Robust



12 V connection



Electric start (with remote
control) and pull starter

